



# grandMA3 onPC DMX-key starter

Art.-No. 4035534



Designed as the perfect first step for the new generation of lighting designers, programmers, and creative minds, the grandMA3 onPC DMX-key starter is the ideal introduction to the world of lighting design. This compact, affordable and powerful small USB device unlocks the full potential of the free of charge grandMA3 onPC software, giving you 1 024 parameters via two DMX outputs without compromising on features or functionality.

The DMX-key starter works instantly with your PC or laptop. Simply plug it in via USB-C, open the grandMA3 onPC software, and start learning, experimenting, and programming your first shows. No setup, configuration or network knowledge is required.

With full access to the complete feature set of the grandMA3 onPC software, you can start learning on the same platform used for the world's biggest shows and productions. It provides an accessible entry point for schools, universities, and other educational facilities, preparing you for professional workflows from day one.

Need some more features? You get a lockable USB-C connector for secure connections wherever you are. The housing is made of robust aluminium. Anti-slip strips at the bottom ensure that you can place the device stably on your work surface. Guide rails with a matching screw set allow for easy mounting in racks or cases.

The grandMA3 onPC DMX-key starter is more than just a device: it's your first step into the MA Lighting universe.



## Features

- Real-time control of 1 024 parameters in combination with grandMA3 onPC
- Lockable USB-C connector
- Status LED
- Robust Aluminium housing
- Anti-slip strips
- Easy mounting with guide rails and screws

## Scope of delivery

| Art.-No. | Article                                                       | Quantity |
|----------|---------------------------------------------------------------|----------|
| 4035958  | MA cable USB 2.0, type C locking screw to type C, length 0.5m | 1        |
| 4035959  | MA set of mounting screws (2x screws M5 x 12 and 2x nut M5)   | 1        |

1x Safety Instructions

## Technical Specifications

|                                          |                                                                    |
|------------------------------------------|--------------------------------------------------------------------|
| <b>Parameters</b>                        | 1 024 (HTP/LTP)                                                    |
| <b>Parameters Mode2</b>                  | not applicable (no Mode2)                                          |
| <b>Operating voltage/ Supply voltage</b> | USB powered (5 V DC)                                               |
| <b>Power</b>                             | max. 2.5 VA                                                        |
| <b>Operating Temperature</b>             | 0 °C up to 40 °C / 32 °F up to 104 °F                              |
| <b>Dimensions</b>                        | 90 x 88 x 38 mm / 3.54 x 3.46 x 1.5 in<br>(width x depth x height) |
| <b>Net weight</b>                        | 0.24 kg / 8.5 oz                                                   |
| <b>Connectors</b>                        | 2 x DMX512-A Out (5pin XLR female)<br>1 x USB 2.0 (type C)         |

## Article

| Art.-No. | Article                       |
|----------|-------------------------------|
| 4035534  | grandMA3 onPC DMX-key starter |

## More product pictures

